

Three Phase Rectifier Bridge

PSD 91F

with fast Recovery Epitaxial Diode (FRED)


$$I_{dAV} = 74 \text{ A}$$

$$V_{RRM} = 800 - 1200 \text{ V}$$

$$t_{rr} = 40 \text{ ns}$$

Preliminary Data Sheet

V_{RSM} V_{DSM} (V)	V_{RRM} V_{DRM} (V)	Type
800	800	PSD 91F/08
1200	1200	PSD 91F/12



Symbol	Test Conditions	Maximum Ratings
I_{dAV}^*	$T_C = 85^\circ\text{C}$, (per module)	74 A
I_{dAVM}		90 A
I_{FSM}	$T_{VJ} = 45^\circ\text{C}$ t = 10 ms (50 Hz), sine	200 A
	$V_R = 0$ t = 8.3 ms (60 Hz), sine	220 A
	$T_{VJ} = T_{VJM}$ t = 10 ms (50 Hz), sine	170 A
	$V_R = 0$ t = 8.3 ms (60 Hz), sine	190 A
$\int i^2 dt$	$T_{VJ} = 45^\circ\text{C}$ t = 10 ms (50 Hz), sine	200 A ² s
	$V_R = 0$ t = 8.3 ms (60 Hz), sine	205 A ² s
	$T_{VJ} = T_{VJM}$ t = 10 ms (50 Hz), sine	145 A ² s
	$V_R = 0$ t = 8.3 ms (60 Hz), sine	150 A ² s
T_{VJ}		-40... + 150 °C
T_{VJM}		150 °C
T_{stg}		-40... + 125 °C
V_{ISOL}	50/60 Hz, RMS t = 1 min	3000 V~
	$I_{ISOL} \leq 1 \text{ mA}$ t = 1 s	3600 V~
M_d	Mounting torque (M4)	1.5 - 1.8 Nm
		14 - 16 lb.in.
Weight	typ.	16 g

Symbol	Test Conditions	Characteristic Value
I_R	$V_R = V_{RRM}, T_{VJ} = T_{VJM}$	≤ 1.0 mA
	$V_R = V_{RRM}, T_{VJ} = 25^\circ\text{C}$	≤ 0.25 mA
V_F	$I_F = 30 \text{ A}, T_{VJ} = 25^\circ\text{C}$	≤ 2.71 V
V_{TO}	For power-loss calculations only	1.31 V
r_T		15 mΩ
R_{thJC}	per diode; DC	0.9 K/W
	per module	0.15 K/W
R_{thJK}	per diode; DC	1.2 K/W
	per module	0.2 K/W
I_{RM}	$I_F = 50 \text{ A}; -di_F/dt = 100 \text{ A}/\mu\text{s}; V_R = 100 \text{ V}$ $L = 0.05 \text{ mH}; T_{VJ} = 100^\circ\text{C}$	typ. 6 A
t_{rr}	$I_F = 1 \text{ A}; -di_F/dt = 200 \text{ A}/\mu\text{s}; V_R = 30 \text{ V};$ $T_{VJ} = 25^\circ\text{C}$	typ. 40 ns
d_s	Creeping distance on surface	11.2 mm
d_A	Creeping distance in air	9.7 mm
a	Max. allowable acceleration	50 m/s ²

Data according to IEC 60747 refer to a single diode unless otherwise stated
*- for resistive load at bridge output

Features

- Package with DCB ceramic base plate
- Isolation voltage 3000 V~
- Planar glass passivated chips
- Low forward voltage drop
- Leads suitable for PC board soldering
- UL registered, E 148688

Applications

- Supplies for DC power equipment
- Input and output rectifier for high frequency
- Battery DC power supplies
- Field supply for DC motors

Advantages

- Easy to mount with two screws
- Space and weight savings
- Improved temperature and power cycling capability
- Low noise switching
- Small and light weight

Package style and outline

Dimensions in mm (1mm = 0.0394")

